



NS series

RFID safety switches with lock



NS series RFID safety switches with lock

Description



These switches are used mainly on machines where the hazardous conditions persist even after the machine has been switched off. Mechanical parts such as pulleys, saw blades, etc., could continue to move after the machine is switched off. Thus, the switches can also be used if individual guards are only to be opened under certain conditions.

Versions with mode 1 and 3 (safety outputs active when guard closed and locked) are interlocks with guard locking acc. to ISO 14119; the product is labelled with the symbol shown.




Series connection of several switches

PL e + SIL 3

One of the most important features of the NS series is the possibility of connecting up to 32 sensors in series, while still maintaining the maximum safety levels PL e laid down in EN 13849-1 and SIL 3 acc. to EN 62061.

This connection type is permissible in safety systems which have a safety module at the end of the chain that monitors the outputs of the last NS switch.


The fact that the PL e safety level can be maintained even with 32 sensors connected in series demonstrates the extremely secure structure of each single device.



Series connection with other devices

PL e + SIL 3

The NS series features two safety inputs and two safety outputs, which can be connected in series with other Pizzato Elettrica safety devices. This option allows the creation of safety chains containing various devices. For example, stainless steel safety hinges (HX BEE1 series), RFID sensors (ST series) and door lock sensors (NG series) can be connected in series while still maintaining the maximum PL e and SIL 3 safety levels.




RFID actuators with high coding level




The NS series is provided with an electronic system based on RFID technology to detect the actuator. This allows to provide each actuator with different coding and makes it impossible to tamper with a device by using another actuator of the same series. Millions of different coding combinations are possible for the actuators. They are therefore classified as high level coded actuators, according to EN ISO 14119.

Dustproof



The switch is provided with a through hole for inserting the actuator. Thanks to this unique feature, any dust that enters the actuator hole can always come out on the opposite side instead of remaining inside. Moreover, the lock pin is provided with a diaphragm seal, making the system suitable for critical environments with a high level of dust.

Head and release devices with variable orientation, not detachable




The upper part of the switch, which contains the release devices, can be rotated and is permanently connected to the lower part, which contains the outputs for the electrical connection. After loosening the fastening screws, the individual modules can be rotated in 90° steps. As a result, a single device can be used to realise various configurations without the installation technician needing to concern himself with the correct assembly of various parts.

The fastening screws are provided with protection caps to prevent dirt build-up and thereby simplify cleaning.


Holding force of the locked actuator

2100 N

The strong interlocking system guarantees a maximum actuator holding force of $F_{1\max} = 2100$ N.



Integrated control devices



The NS series switches are also available in a version with a long housing, that has room for fitting 1 to 4 control devices, with the relevant contact blocks, on the same body of the safety device. This version has the same modular and orientation features as the NS switches.

To meet requirements for a range of uses, a number of different colour and types of control devices can be adopted such as, for example: buttons, emergency stop buttons, indicator lights, selector switches. Button lenses are customizable by laser engraving.

The control devices can be illuminated and protrude only slightly out of the housing thanks to the recessed housing hole.


The result is a compact solution with direct access to control devices without needing to install them separately on the switch panel or in their own housing.

Six LEDs for immediate diagnosis




As the LEDs have been designed for quick immediate diagnosis, the status of each input and output is highlighted by one specific LED. This makes it possible to quickly identify the interruption points in the safety chain, which device is released, which guard is opened and any errors inside the device. All of this at a glance, without needing to decode complex flashing sequences.

Holding force of the unlocked actuator




The inside of each switch features a device which holds the actuator in its closed position. Ideal for all those applications where several guards are unlocked simultaneously, but only one is actually opened. The device keeps all the unlocked guards in their position with a retaining force of approx. 20 N, stopping any vibrations or gusts of wind from opening them.

Function for protecting against recoil forces



If a guard is closed too quickly or with so much force that the recoil would cause it to open again, a special function in the NS switch prevents locking. This function prevents the immediate locking of the guard if the lock signal is applied. This protects the switch against recoil forces that occur during instantaneous locking, thus avoiding possible damage to the device.

Key release device and escape release button



The key release device (auxiliary release) is used to permit unlocking of the actuator only by personnel in possession of the key. The device also functions with no power supply and, once actuated, prevents the guard from being locked.

The escape release button allows actuator release and immediate opening of the guard. Generally used in machines

within which an operator could inadvertently become trapped, it faces towards the machine interior, to allow the operator to exit even in the event of a power failure. The button has two stable states and can be freely extended in length with suitable extensions (see accessories).

Both devices can be positioned on the four sides of the switch. As a result, it can be installed both towards the interior and towards the exterior of the machine.

Three safety output actuation modes

MODE 1

MODE 2


MODE 3

The device is available with 3 different actuation modes for safety outputs:

- mode 1: safety outputs active with inserted and locked actuator, for machines with inertia;
- mode 2: safety outputs active with inserted actuator, for machines without inertia;


- mode 3: a first safety output active with actuator inserted and locked and a second safety output active with actuator inserted, for special applications.

Protection against tampering



Each actuator of the NS series is supplied with four protection caps. Not only do the caps prevent dirt from accumulating and simplify cleaning, they also block access to the fastening screws of the actuator. As a result, standard screws can be used instead of tamper-proof screws.

Jointed actuator for inaccurately closing guards




All NS series actuators are articulated, thereby allowing the actuator pin to be safely guided into the switch through the centring hole. As a result, the actuator and switch do not need to be precisely aligned during installation. In addition, the device can thereby be used on guards with a minimum actuation radius of 150 mm without the actuation pin needing to be angled.

Front and side mounting

Integrated in the housing of the NS series is a hole for inserting the actuator pin. Fixing holes are also provided in the robust body for front and side mounting.

This makes it easier to mount the switch during lateral installation: the switch is directly mounted without needing to rotate the module that

contains the hole for inserting the actuator pin. The fixing holes can be sealed with the protection caps provided for this purpose. Dirt deposits and tampering attempts are thereby prevented.



High protection degree

IP69K

IP67

These devices are designed to be used in the toughest environmental conditions and they pass the IP67 immersion test acc. to EN 60529. They can therefore be used in all environments where maximum protection degree of the housing is required. Due to their special design, these devices are suitable for use in equipment subjected to cleaning with high pressure hot water jets. These devices meet the IP69K test requirements according to ISO 20653 (water jets with 100 bar and 80°C).


External device monitoring

EDM

On request, the switch can be supplied with EDM function (External Device Monitoring). In this case, the switch itself checks the proper function of the devices connected to the safety outputs. These devices (usually relays or safety contactors) must send a feedback signal to the EDM input, which checks that the received signal is consistent with the state of the safety outputs.

NS series RFID safety switches with lock

Selection diagram





Code structure

Attention! The feasibility of a code number does not mean the effective availability of a product. Please contact our sales office.

article **NS D4AZ1SMK-F41N001E36LP30VS01** options

Operating principle

D	locked actuator with de-energised solenoid, mode 1
E	locked actuator with energised solenoid, mode 1
G	locked actuator with de-energised solenoid, mode 2
H	locked actuator with energised solenoid, mode 2
L	locked actuator with de-energised solenoid, mode 3
M	locked actuator with energised solenoid, mode 3

Inputs and outputs

3	2 safety inputs IS1, IS2 2 safety outputs OS1, OS2 1 signalling output O3: actuator inserted 1 signalling output O4: actuator locked 2 solenoid activation inputs IE1, IE2 1 reset input I3 Note: Supplied only together with actuator
4	2 safety inputs IS1, IS2 2 safety outputs OS1, OS2 1 signalling output O3: actuator inserted 1 signalling output O4: actuator locked 2 solenoid activation inputs IE1, IE2 1 programming / reset input I3
5	2 safety inputs IS1, IS2 2 safety outputs OS1, OS2 1 signalling output O3: actuator inserted 1 signalling output O4: actuator locked 2 solenoid activation inputs IE1, IE2 1 programming / reset input I3 1 feedback input EDM I5 Note: Not available with mode 3

Auxiliary release at front and back

AZ	release by means of screwdriver at front ⁽¹⁾
ST	key release at front ⁽¹⁾
SE	key release at front and escape release button at back ⁽¹⁾
CE	release by means of screwdriver at front and escape release button at back ⁽¹⁾
ZZ	without release ⁽²⁾
TE	Without release at front and escape release button at back ⁽²⁾

(1) only available for operating principle D, G and L

(2) only available for operating principle E, H and M

Output direction, connections

D	cable or connector, lateral
S	cable or connector, axial

Code structure for actuator

VN NS-F40

Actuator

F40	low level coded actuator the switch recognises any type F40 actuator
F41	high level coded actuator the switch recognises one single type F41 actuator

Software versions ⁽¹⁾

VS01	O4: fault signalling output
VS02	O3: inverted signalling output O4: inverted signalling output
VS03	O3: fault signalling output
VS04	O3: generates a voltage dip (0.2ms) when the device is blocked

(1) Available for non-safety inputs and outputs only.

Release button length

	for max. 15 mm wall thickness (standard)
LP30	for max. 30 mm wall thickness
LP40	for max. 40 mm wall thickness
LP50	for max. 50 mm wall thickness

Actuator extraction force

	actuator extraction force 20 N (standard)
E36	actuator freely removable
E37	actuator extraction force 40 N

Button configurations

N001	configuration 001
N002	configuration 002
N002	configuration 003
...	other configurations on request

Actuator

F40	low level coded actuator VN NS-F40 the switch recognises any type F40 actuator
F41	high level coded actuator VN NS-F41 the switch recognises one single type F41 actuator

Connection type

K	integrated connector (standard)
0.2	cable, length: 0.2 m, with M12 connector
2	cable, length: 2 m (standard)
...
10	cable, length: 10 m

Cable or connector type

A	PVC cable 12x0.14 mm ²
B	PVC cable 8x0.34 mm ² , for stand-alone connections ⁽¹⁾
E	PUR cable, halogen-free, 8x0.34 mm ² , for stand-alone connections ⁽¹⁾
M	M12 connector, 12-pole (standard)
P	M12 connector, 8-pole, for stand-alone connections ⁽¹⁾
Q	M12 connector, 8-pole, for series connection with Y connectors ⁽²⁾
R	two M12 connectors (12-pole + 12-pole) ⁽³⁾
S	M23 connector, 12-pole ⁽³⁾
T	M23 connector, 19-pole ⁽³⁾


(1) without inputs IS1, IS2, I5 and without output O4

(2) without inputs IE2, I3, I5 and without output O3

(3) only for items with integrated control devices

For the complete list of possible combinations please contact our technical department.

NS series RFID safety switches with lock



Main features

- Actuation without contact, using RFID technology
- Digitally coded actuator
- SIL 3 and PL e also with series connection of up to 32 devices
- Max. actuator holding force: 2100 N
- SIL 3 and PL e with a single device
- Protection degree up to IP67 and IP69K
- 6 signalling LEDs

Quality marks:



EC type examination certificate: M6A0751570029
 UL approval: E131787
 TÜV SÜD approval: Z10 075157 0025
 EAC approval: RU C-IT.YT03.B.00035/19

In compliance with standards:

EN ISO 14119, EN 60947-5-3, EN 60947-1, EN 60204-1, EN ISO 12100, EN 60529, EN 61000-6-2, EN 61000-6-3, EN 61508-1, EN 61508-2, EN 61508-3, EN ISO 13849-1, EN ISO 13849-2, EN 62061, EN 61326-1, EN 61326-3-1, EN IEC 63000, ETSI 301 489-1, ETSI 301 489-3, ETSI 300 330-2, UL 508, CSA 22.2 No.14

Compliance with the requirements of:

Machinery Directive 2006/42/EC, EMC Directive 2014/30/EC, RED Directive 2014/53/EU, RoHS directive 2011/65/EU, FCC Part 15.

Features approved by UL

Electrical ratings: 24 Vdc Class 2, 0,25 A (versions without control devices), 0,3 A (versions with control devices). Input Supplied by 24 Vdc, Class 2 Source or limited voltage limited energy. Input NS side: 24 Vdc, 0,15 A. Input BN side: 24 Vdc, 0,048 A max. (maximum four leds). Output NS side: 2 output 24 Vdc, 0,25 A plus 2 output 24 Vdc, 0,1 A. Output BN side: 24 Vac/dc Class 2 0,25 A Pilot Duty (maximum four actuators, with maximum six contacts, NO or NC or both) or 0,18 A Pilot Duty (maximum four actuators, with maximum eight contacts, NO or NC or both). Environmental ratings: Types 1, 4X, 12, 13 (versions without control devices), Type 1 (versions with control devices).

Features approved by TÜV SÜD

Protection degree: IP67, IP69K
 Ambient temperature: -20°C...+50°C
 PL, category: Cat 2 / 4, PL d / e
 SIL: SIL 2/3, SIL CL 2/3
 In compliance with standards: EN 60947-5-3:2013, EN 61508-1:2010 (SIL 2 / 3), EN 61508-2:2010 (SIL 2 / 3), EN 61508-3:2010 (SIL 2 / 3), EN ISO 14119:2013, EN 62061:2015/A2:2015 (SIL CL 2 / 3), EN ISO 13849-1:2015 (Cat. 2 / 4, PL d / e). Complies with machinery directive 2006/42/EC. Please contact our technical department for the list of approved products.

Technical data

Housing made of glass fibre reinforced technopolymer, self-extinguishing and shock-proof
 Versions with 12x0.14 mm² or 8x0.34 mm² integrated cable, length 2 m, other lengths from 0.5 to 10 m on request
 Versions with integrated M12 stainless steel connector
 Versions with 0.2 m cable and M12 connector, other lengths from 0.1 ... 3 m on request
 Protection degree:
 Protection degree with control devices:

IP67 acc. to EN 60529
 IP69K acc. to ISO 20653 (Protect the cables from direct high-pressure and high-temperature jets)
 IP65 acc. to EN 60529

General data

Safety parameters	SIL	PL	Cat.	DC	PFH _D	MTTF _D
Monitoring function: actuator locked - Mode 1	3	e	4	High	1.23E-09	2657
Monitoring function: actuator present - Mode 2	3	e	4	High	1.22E-09	1840
Monitoring function: actuator locked - Mode 3	2	d	2	High	1.50E-09	2627
Monitoring function: actuator present - Mode 3	2	d	2	High	1.49E-09	3987
Dual-channel control for locking function of the actuator	3	e	4	High	2.04E-10	2254
Single-channel control for locking function of the actuator	2	d	2	High	2.04E-10	2254

Interlock, no contact, coded, with guard locking:
 Level of coding acc. to EN ISO 14119:

type 4 acc. to EN ISO 14119

low with F40 actuator

High with F41 actuator

20 years

-20°C ... +50°C

600 operating cycles/hour

1 million operating cycles

0.5 m/s

1 mm/s

2100 N acc. to EN ISO 14119

1615 N acc. to EN ISO 14119

4 mm

~ 20 N

Power supply electrical data

Rated operating voltage U_e SELV:
 Operating current at U_e voltage:

24 Vdc ±10%

40 mA min., 0,4 A max. with activated solenoid;
 1,2 A with activated solenoid and all outputs at maximum power

32 Vdc

1,5 kV

type gG fuse 2 A or equivalent device

III

1 million operating cycles

100% ED (continuous operation)

9 W max.

3 acc. to EN 60947-1

Electrical data of inputs IS1/IS2/I3/IE1/IE2/I5/EDM

Rated operating voltage U_{e1}: 24 Vdc
 Rated current consumption I_{e1}: 5 mA

Electrical data of OS1/OS2 safety outputs

Rated operating voltage U_{e2}: 24 Vdc
 Output type: PNP type OSSD

0.25 A

0.5 mA

0.25 A

DC13; U_{e2}=24 Vdc, I_{e2}=0.25 A

Yes

Yes

1.1 A

< 300 µs

Duration of the deactivation impulses at the safety outputs: < 300 µs

Permissible maximum capacitance between outputs: < 200 nF

Permissible maximum capacitance between output and ground:

Activation time of safety outputs OS1 and OS2 after deactivation of safety inputs IS1, IS2:

typically 7 ms, max. 15 ms

Activation time upon unlocking the actuator:

typically 7 ms, max. 12 ms

Activation time upon removal of the actuator:

typically 120 ms, max. 200 ms

Maximum delay for EDM status change: 500 ms

Electrical data of O3/O4 signalling outputs

Rated operating voltage U_{e3}: 24 Vdc
 Output type: PNP
 Maximum current per output I_{e3}: 0.1 A
 Utilization category: DC13; U_{e3}=24 Vdc, I_{e3}=0.1 A
 Short circuit detection: No
 Overcurrent protection: Yes
 Internal self-resettable protection fuse: 1.1 A

RFID sensor data


Assured operating distance S_{ao}: 2 mm
 Assured release distance S_{ar}: 6 mm (actuator not locked)
 10 mm (actuator locked)
 Rated operating distance S_n: 3 mm
 Repeat accuracy: ≤ 10 % S_n
 Differential travel: ≤ 20 % S_n
 RFID transponder frequency: 125 kHz
 Max. switching frequency: 1 Hz



Actuation mode of the OS1 and OS2 safety outputs


Mode 1	Mode 2	Mode 3
Safety outputs OS1 and OS2 are active when the actuator is inserted and locked.	Safety outputs OS1 and OS2 are active when the actuator is inserted.	Safety output OS1 is active when the actuator is inserted and locked and IS1 is active. Safety output OS2 is active when the actuator is inserted and IS2 is active.
In case of machines with or without inertia of the dangerous elements. Safety category of the safety outputs: PL e, SIL 3.	In case of machines without inertia of the dangerous elements. Safety category of the safety outputs: PL e, SIL 3.	In case of machines with or without inertia of the dangerous elements. Safety category of the safety outputs: PL d, SIL 2.

Selection table for switches with high level coded actuators



Operating principle	Locked actuator with de-energised solenoid. With screwdriver release	Locked actuator with energised solenoid	Locked actuator with de-energised solenoid. With key release	Locked actuator with de-energised solenoid. With key release and escape release button	Locked actuator with de-energised solenoid. With screwdriver release and escape release button	Locked actuator with energised solenoid. With escape release button
Mode 1	NS D4AZ1SMK-F41	NS E4ZZ1SMK-F41	NS D4ST1SMK-F41	NS D4SE1SMK-F41	NS D4CE1SMK-F41	NS E4TE1SMK-F41
Mode 2	NS G4AZ1SMK-F41	NS H4ZZ1SMK-F41	NS G4ST1SMK-F41	NS G4SE1SMK-F41	NS G4CE1SMK-F41	NS H4TE1SMK-F41
Mode 3	NS L4AZ1SMK-F41	NS M4ZZ1SMK-F41	NS L4ST1SMK-F41	NS L4SE1SMK-F41	NS L4CE1SMK-F41	NS M4TE1SMK-F41

Selection table for switches




Operating principle	Locked actuator with de-energised solenoid. With screwdriver release	Locked actuator with energised solenoid	Locked actuator with de-energised solenoid. With key release	Locked actuator with de-energised solenoid. With key release and escape release button	Locked actuator with de-energised solenoid. With screwdriver release and escape release button	Locked actuator with energised solenoid. With escape release button
Mode 1	NS D4AZ1SMK	NS E4ZZ1SMK	NS D4ST1SMK	NS D4SE1SMK	NS D4CE1SMK	NS E4TE1SMK
Mode 2	NS G4AZ1SMK	NS H4ZZ1SMK	NS G4ST1SMK	NS G4SE1SMK	NS G4CE1SMK	NS H4TE1SMK
Mode 3	NS L4AZ1SMK	NS M4ZZ1SMK	NS L4ST1SMK	NS L4SE1SMK	NS L4CE1SMK	NS M4TE1SMK

To order a product with lateral connection replace character **S** with character **D** in the order codes shown above. Example: NS D4AZ1SMK → NS D4AZ1SMK

To order a product with EDM input replace number **4** with number **5** in the codes shown above. Example: NS D4AZ1SMK → NS D5AZ1SMK

Legend: interlock with lock monitoring acc. to EN ISO 14119

Selection table for actuators



The use of RFID technology in NS series devices makes them suitable for several applications. Pizzato Elettrica offers two different versions of actuators, in order to best suit customers' specific needs. Type F40 actuators are all encoded with the same code. This implies that a device associated with an actuator type F40 can be activated by other actuators type F40.


Type F41 actuators are always encoded with different codes. This implies that a device associated with an actuator type F41 can be activated only by a specific actuator. Another F41 type actuator will not be recognised by the device until a new association procedure is carried out (reprogramming). After reprogramming, the old actuator F41 will no longer be recognized. Reprogramming of the actuator can be performed repeatedly.

Level of coding acc. to EN ISO 14119	Article
low	VN NS-F40
high	VN NS-F41


NS series RFID safety switches with lock

Complete safety system

The use of complete and tested solutions guarantees the electrical compatibility between the NS series switches and the safety modules from Pizzato Elettrica, as well as high reliability. The switches have been tested with the modules listed in the adjacent table.




NS series switches can be used as individual devices provided that the safety outputs be evaluated by a Pizzato Elettrica safety module (see table for combinable safety modules).



Possibility of series connection of multiple switches for simplifying the wiring of the safety system, whereby only the outputs of the last switch are evaluated by a Pizzato Elettrica safety module (see table with compatible safety modules). Each NS series switch is provided with two signalling outputs which are activated when the guard is closed (O3) or locked (O4). Depending on the specific requirements of the system that has been realised, the signals of the signalling outputs can be evaluated by a PLC.

Switches	Compatible safety modules	Safety module output contacts		
		Instantaneous safety contacts	Delayed safety contacts	Signalling contacts
NS ••••1•••	CS AR-05•••••	3NO	/	1NC
	CS AR-06•••••	3NO	/	1NC
	CS AR-08•••••	2NO	/	/
	CS AT-0•••••	2NO	2NO	1NC
	CS AT-1•••••	3NO	2NO	/
	CS MP•••••	page 309 of the General Catalogue Safety		
	CS MF•••••	page 341 of the General Catalogue Safety		


All NS series switches can be connected, provided that compatibility is checked, to safety modules or safety PLCs with OSSD inputs.



Possibility of series connection of multiple switches for simplifying the wiring of the safety system, whereby only the outputs of the last switch are evaluated by a Pizzato Elettrica safety module of the CS MP series. Both the safety-relevant evaluation and the evaluation of the signalling outputs are performed by the CS MP series.

The examples listed above refer to applications with NS ••••1•••.

Internal block diagram



The diagram on the side represents the 7 logic functions which interact inside the device. Function f0 is a basic function and includes the monitoring of the power supply as well as internal, cyclical tests. Function f1 monitors the status of the device inputs, whereas function f2 monitors the presence of the actuator within the detection areas of the switch.

Function f4 checks the actuator lock condition.

Function f3 is intended to activate or deactivate the safety outputs and check for any faults or short circuits in the outputs.

In the EDM versions, the f5 function verifies the consistency of the EDM signal during safety output state changes.

The safety-related function, which combines the sub-functions mentioned above, activates the safety outputs according to the chosen operating mode:


- Both safety outputs OS1/OS2 for switches in mode 1 are activated only if both IS1/IS2 safety inputs are active and the actuator is inserted and locked;
- Both safety outputs OS1/OS2 for switches in mode 2 are activated only if both IS1/IS2 safety inputs are active and the actuator is inserted;
- The safety output OS1 for switches in mode 3 is activated only if the IS1 safety input is active and the actuator is inserted and locked, whereas the safety output OS2 is activated only if the IS2 safety input is active and the actuator is inserted.

The f6 function verifies the coherence of the enable/disable signals of the actuator lock command.

The status of each function is displayed by the corresponding LED (PWR, IN, OUT, ACT, LOCK, EDM), in such a way that the general device status becomes immediately obvious to the operator.

LED	Function
PWR	Power supply / self-diagnosis
IN	status of safety inputs
OUT	status of safety outputs
ACT	actuator state
LOCK	actuator locked
EDM	state of EDM inputs (NS ••••1•••)

Actuation sequence in mode 1



The switch is supplied with power (PWR LED on, green), the IS1 and IS2 inputs are enabled (IN LED on, green), the OS1 and OS2 safety outputs are disabled (OUT LED off). The actuator is outside of the actuation zone (LED ACT off).

When the actuator is brought inside the safe actuation area (dark grey area), the switch turns on the ACT LED (green). In this position, the O3 signalling output (door-closed) is activated. The actuator is not locked (LOCK LED off).

The IE1, IE2 inputs can be used to lock the actuator (LOCK LED on, green). The OS1 and OS2 safety outputs are enabled (OUT LED on, green). The O4 signalling output is activated at the same time. The safe actuation area is extended in order to allow greater play for the actuator.

The IE1, IE2 inputs can be used to unlock the actuator (LOCK LED off). The switch disables the OS1 and OS2 safety outputs and turns off the OUT LED. The O4 signalling output is deactivated at the same time. The safe actuation area returns to the initial values.

PWR ACT
IN LOCK
OUT

When the actuator leaves the actuation limit area, the device turns off the ACT LED and the O3 signalling output.

PWR ACT
IN LOCK
OUT

Actuation sequence in mode 2 and mode 3

In contrast to the above mode 2 description, the safety outputs OS1 and OS2 are activated when the actuator is detected, and deactivated when the actuator is no longer detectable, in mode 3, the OS1 safety output is active with inserted and locked actuator and IS1 active, the OS2 safety output is active with inserted actuator and IS2 active.

Operating states

PWR LED	IN LED	OUT LED	ACT LED	LOCK LED	EDM LED (a)	Device state	Description
○	○	○	○	○	○	OFF	Device switched off.
●	●	●	●	●	●	POWER ON	Internal tests upon activation.
●	○	○	*	*	●	RUN	Safety inputs of the device not active.
●	●	*	*	*	*	RUN	Activation of safety inputs.
●	●	○	*	*	*	RUN	Safety inputs incoherence. Recommended action: check for presence and/or wiring of inputs.
●	*	*	*	●	*	RUN	Incoherence of solenoid activation inputs IE1, IE2. Recommended action: check for presence and/or wiring of inputs.
●	*	*	*	●	*	RUN	Auxiliary release activated. Deactivate the auxiliary release to lock the actuator
●	*	*	●	*	*	RUN	Actuator in safe area. O3 signalling output active.
●	*	*	●	●	○	RUN	Actuator in safe area and locked; O3 and O4 outputs active.
●	●	●	●	●	○	RUN	Mode 1 Activation of safety inputs IS1, IS2. Actuator in safe area and locked. O3, O4, OS1 and OS2 outputs active.
●	●	●	●	*	○	RUN	Mode 2 Activation of safety inputs IS1, IS2. Actuator in safe area. O3, OS1 and OS2 outputs active.
●	●	●	●	●	○	RUN	Mode 3 Actuator present, guard closed and locked, IS1 enabled, IS2 disabled, OS1 enabled, OS2 disabled
●	●	●	●	●	○	RUN	Mode 3 Actuator present, guard closed and not locked, IS1 and IS2 enabled, OS1 disabled, OS2 enabled
●	*	*	*	*	*	RUN	Rapid flashing: supply voltage too high. Slow flashing: temperature outside admissible range
●	*	●	*	*	*	ERROR	Error on safety outputs. Recommended action: check for any short circuits between the outputs, outputs and ground or outputs and power supply, then restart the device.
●	○	○	●	●	○	ERROR	Actuator detection error. Check the physical integrity of the device and, in case of failure, please replace the entire device. If undamaged, realign the actuator with the switch and restart the device.
●	○	○	○	○	○	ERROR	Internal error. Recommended action: restart the device. If the failure persists, replace the device.
●	*	○	*	*	●	RUN	EDM signal active (external relay off) ^a
●	●	●	●	●	○	RUN	EDM signal not active (external relay on) ^a
●	○	○	○	○	●	ERROR	Error in the EDM ^a function

Legend:

○ = off

● = on

● = blinking


● = changing colours

* = indifferent


(a) Available for NS •5••1••• versions only

NS series RFID safety switches with lock

External device monitoring (EDM)



The NS 5••1•• version, in addition to maintaining the operating and safety characteristics of the NS series, allows control of **forcibly guided NC contacts of contactors or relays** controlled by the safety outputs of the switch itself. As an alternative to the relays or contactors you can use Pizzato Elettrica expansion modules CS ME-03 (see page 267). This check is carried out via the EDM input (External Device Monitoring as defined in EN 61496-1) of the switch.




This version, with the IS safety inputs, **can be used at the end of a series of NS switches, up to a maximum number of 32 devices**, while maintaining the maximum PL e safety level and acc. to EN ISO 13849-1 and SIL 3 safety level acc. to EN 62061. This solution allows you to dispense with the safety module connected to the last device in the chain. If present, the EDM function must be used.

Connection with safety modules

Connections with CS AR-08•••• safety modules

Input configuration with monitored start


2 channels / Category 4 / up to SIL 3 / PL e



Connections with CS AR-05•••• / CS AR-06•••• safety modules

Input configuration with manual start (CS AR-05••••) or monitored start (CS AR-06••••)


2 channels / Category 4 / up to SIL 3 / PL e



Connections with CS AT-0••••• / CS AT-1••••• safety modules

Input configuration with monitored start


2 channels / Category 4 / up to SIL 3 / PL e



Connections with CS MF•••••, CS MP••••• safety modules

The connections vary according to the program of the module

Category 4 / up to SIL 3 / PL e




Application example on page 307,
General Catalogue Safety 2021-2022

Series connection of several switches


Monitoring function: actuator locked
2 channels / Category 4 / up to SIL 3 / PL e

Single-channel control for locking function of the actuator
1 channel / Category 2 / up to SIL 2 / PL d



Monitoring function: actuator locked
2 channels / Category 4 / up to SIL 3 / PL e

Dual-channel control for locking function of the actuator
2 channels / Category 4 / up to SIL 3 / PL e




Safety switch internal connections

Versions with connector			Versions with cable			Connection
NS *****M*	NS *****P*	NS *****Q*	NS *****A*	NS *****B*, NS *****E*		
M12 connector, 12-pole	M12 connector, 8-pole stand-alone connection	M12 connector, 8-pole series connection with "Y" connectors	Cable 12x0.14 mm ² outer diameter 6 mm	Cable 8x0.34 mm ² outer diameter 7 mm		
3	3	3	White	Blue	A2	Supply input 0 V
10	8	8	Purple	Red	IE1	Solenoid activation input
12	5	/	Red-Blue	Purple	IE2	Solenoid activation input
5	2	/	Pink	Black	O3	Signalling output, actuator inserted
9	/	5(b)	Red	/	O4	Signalling output, actuator inserted and locked
8	6	/	Grey	purple-white	I3	Actuator programming input / reset
1	1	1	Brown	Brown	A1	Supply input +24 Vdc
2	/	2	Blue	/	IS1	Safety input
6	/	6	Yellow	/	IS2	Safety input
11	/	/	Grey-Pink	/	I5	EDM input (a)
4	4	4	Green	Red-White	OS1	Safety output
7	7	7	Black	Black-White	OS2	Safety output

(a) Available for NS *****1*** version only

(b) Available for 8-pole connector, not available for the end of a chain with Y connectors.




Series connection

To simplify series connections of the devices, various M12 connectors are available that allow complete wiring.


This solution significantly reduces installation times while at the same time maintaining the maximum safety levels PL e and SIL 3 for the interlocking function.

For further information see page 366 of the General Catalogue Safety 2021-22.



NS series RFID safety switches with lock

Switch with integrated control device unit for 1 device



NS *****SRK-N110			NS *****SRK-N111			NS *****SRK-N112			
	Description	Colour	Description	Colour	Diagram		Description	Colour	Diagram
Device 1	Emergency stop button with rotary release 2NC	red	B2 B5			Device 1	Illuminated button, spring-return 1NO	white	B2 B3
			B1 B4						B1 B5
Connector	1 x M12, 12-pole + 1 x M12, 5-pole axial	/				Device 1	1 x M12, 12-pole + 1 x M12, 5-pole axial	/	
			A B						A B


Internal connections (versions with integrated control device unit for 1 device)

	Connection		NS *****SRK-N110	NS *****SRK-N111	NS *****SRK-N112
A1	Supply input +24 Vdc				
A2	Supply input 0 Vdc				
IS1	Safety input				
OS1	Safety output				
IS2	Safety input				
OS2	Safety output				
IE1	Solenoid activation input for double channel mode				
IE2	Solenoid activation input for double channel mode				
O3	Signalling output, actuator inserted				
O4	Signalling output, actuator inserted and locked				
I3	Actuator programming input / reset				
I5	EDM input (a)				
I4	Solenoid activation input for single channel mode				

(a) Available for NS *****SRK-N110 version only



Switch with integrated control device unit for 2 devices



NS *****SRK-N113			NS *****SRK-N114			NS *****SRK-N115		
	Description	Colour	Description	Colour	Diagram	Description	Colour	Diagram
Device 1	Illuminated button, spring-return 1NO	white	Illuminated button, spring-return 1NO	blue		Illuminated button, spring-return 1NO	white	
Device 2	Emergency stop button with rotary release 2NC	red	Emergency stop button with rotary release 2NC	red		Emergency stop button with rotary release 2NC	red	
Connector	1 x M12, 12-pole + 1 x M12, 8-pole axial	/	1 x M12, 12-pole + 1 x M12, 8-pole axial	/		1 x M12, 12-pole + 1 x M12, 8-pole axial	/	


Internal connections (versions with integrated control device unit for 2 devices)

Connection		NS *****SRK-N113	NS *****SRK-N114	NS *****SRK-N115
A1	Supply input +24 Vdc			
A2	Supply input 0 Vdc			
IS1	Safety input			
OS1	Safety output			
IS2	Safety input			
OS2	Safety output			
IE1	Solenoid activation input for double channel mode			
IE2	Solenoid activation input for double channel mode			
O3	Signalling output, actuator inserted			
O4	Signalling output, actuator inserted and locked			
I3	Actuator programming input / reset			
I5	EDM input (a)			

(a) Available for NS *****SRK-N113 version only

NS series RFID safety switches with lock

Switch with integrated control device unit for 3 devices



NS *****SRK-N001			NS *****SRK-N002			NS *****STK-N003				
	Description	Colour		Description	Colour		Description	Colour		
Device 1	Illuminated button, spring-return 1NO	white	B4 B1 B5 B1 B7 B1	B3 B2 B3 B6 B3 B12	LED	Device 1	Illuminated button, spring-return 1NO	white		
Device 2	Illuminated button, spring-return 1NO	blue	E- B1 B5 B1	B4 B1 B5 B1 B7 B1	LED	Device 2	Illuminated button, spring-return 1NO	blue		
Device 3	Illuminated button, spring-return 1NO	yellow	E- B1	B4 B1 B5 B1 B7 B12	LED	Device 3	Emergency stop button with rotary release 2NC	red		
Connector	2x M12, 12-pole, axial	/	A B	Connector	2x M12, 12-pole, axial	/	A B	Connector	Spring-return button 1NO	black
									Emergency stop button with rotary release 2NC	red
									M23, 19-pole, axial	/


Internal connections (versions with integrated control device unit for 3 devices)

Connection	
A1	Supply input +24 Vdc
A2	Supply input 0 Vdc
IS1	Safety input
OS1	Safety output
IS2	Safety input
OS2	Safety output
IE1	Solenoid activation input for double channel mode ^(b)
IE2	Solenoid activation input for double channel mode ^(b)
O3	Signalling output, actuator inserted
O4	Signalling output, actuator inserted and locked
I3	Actuator programming input / reset
I5	EDM input ^(a)
I4	Solenoid activation input for single channel mode ^(c)


(a) Available for NS *****1000-N000 version only

(b) For versions with double M12 connector, 12-pole

(c) For versions with M23 connector, 19-pole



Switch with integrated control device unit for 4 devices



NS *****SRK-N004			NS *****SRK-N005			NS *****SRK-N006		
	Description	Colour		Description	Colour		Description	Colour
Device 1	Illuminated button, spring-return 1NO	green		Illuminated button, spring-return 1NO	white		Illuminated button, spring-return 1NO	white
Device 2	Illuminated button, spring-return 1NO	red		Illuminated button, spring-return 1NO	blue		Spring-return button 1NO	black
Device 3	Illuminated button, spring-return 1NO	white		Illuminated button, spring-return 1NO	yellow		Indicator light	green
Device 4	Illuminated 2-position selector switch 1NO	black		Emergency stop button with rotary release 2NC	red		Emergency stop button with rotary release 2NC	red
Connector	2x M12, 12-pole, axial	/		2x M12, 12-pole, axial	/		2x M12, 12-pole, axial	/

Internal connections (versions with integrated control device unit for 4 devices)

Connection		NS *****SRK-N004	NS *****SRK-N005	NS *****STK-N006
Safety switch	<p>A1 Supply input +24 Vdc</p> <p>A2 Supply input 0 Vdc</p> <p>IS1 Safety input</p> <p>OS1 Safety output</p> <p>IS2 Safety input</p> <p>OS2 Safety output</p> <p>IE1 Solenoid activation input for double channel mode</p> <p>IE2 Solenoid activation input for double channel mode</p> <p>O3 Signalling output, actuator inserted</p> <p>O4 Signalling output, actuator inserted and locked</p> <p>I3 Actuator programming input / reset</p> <p>I5 EDM input (a)</p>			


(a) Available for NS *****SRK-N004 version only

NS series RFID safety switches with lock

Dimensional drawings


Device

NS ••AZ••MK
NS ••ZZ••MK




Device

NS ••ST••MK
NS ••SE••MK




Actuator

VN NS-F4•




Device

NS ••AZ••S•K-N•••
NS ••ZZ••S•K-N•••




Device

NS ••ST••S•K-N•••
NS ••SE••S•K-N•••




NS ••CE••S•K-N•••
NS ••TE••S•K-N•••

Device
NS ••AZ••S•K-N•••
NS ••ZZ••S•K-N•••



Device
NS ••ST••S•K-N•••
NS ••SE••S•K-N•••




X = see page 15,


Y = 47.5 mm (versions with 3 buttons); Y = 31.7 mm (versions with 4 buttons)

Output type


M12 connector, axial




Two M12 connectors, axial







M12 connector, lateral




M23 connector, axial



Extensions for release button

Article	Description	Drawing
VN NG-LP30	Metal extension for release button. For max. wall thickness of 30 mm	
VN NG-LP40	Metal extension for release button. For max. wall thickness of 40 mm	
VN NG-LP50	Metal extension for release button. For max. wall thickness of 50 mm	
VN NG-LP60	Metal extension for release button. For max. wall thickness of 60 mm	
VN NG-ERB	Red metal release button	




- Metal extensions can be combined with one another to achieve the desired length.
- Do not exceed an overall length of 100 mm between the release button and the switch.
- Use medium-strength thread locker to secure the extensions.

→ The 2D and 3D files are available at www.pizzato.com


All values in the drawings are in mm

Electrical connector configurations


Two M12 connectors, 12-pole + M12, 5-pole




Two M12 connectors, 12-pole + M12, 8-pole



Two M12 connectors, 12-pole



M23 connector, 19-pole



NS series RFID safety switches with lock

Technical data of the integrated control devices

General data

Protection degree:	IP65 acc. to EN 60529
Mechanical endurance:	
Spring-return button:	1 million operating cycles
Emergency stop button:	50,000 operating cycles
Selector switch:	300,000 operating cycles
Key selector switch:	50,000 operating cycles
	30,000 operating cycles including removal of the key
Safety parameter B _{10D} :	100,000 (emergency stop button)

Actuating force

Spring-return button:	4 N min	100 N max.
Emergency stop button:	20 N min	100 N max.
Selector switch:	0.1 Nm min	1.5 Nm max.
Key selector switch:	0.1 Nm min	1.3 Nm max.

Contact blocks of the control devices

Material of the contacts:	silver contacts
Contact type:	Self-cleaning contacts with double interruption

Electrical data:

Thermal current I _{th} :	1 A
Rated insulation voltage U _i :	32 Vac/dc
Rated impulse withstand voltage U _{imp} :	1.5 kV
LED supply voltage:	24 Vdc ± 15%
LED supply current:	12 mA per LED

Utilization category of the contact block:

Direct current:	DC-13
U _e (V)	24
I _e (A)	0.55

In compliance with standards:

IEC 60947-5-1, IEC 60947-5-5, EN ISO 13850

⚠ Installation for safety applications:

Always connect the safety circuit to the **NC contacts** (normally closed contacts) as stated in standard EN 60947-5-1.

Electrical data of M12 connector:

Max. operating voltage:	32 Vac/dc
Max. operating current:	1.5 A max.

Electrical data of M23 connector:

Max. operating voltage:	32 Vac/dc
Max. operating current:	3 A max.

Accessories

Article	Description
VF KLB300	 <p>Set of two locking keys Extra copy of the locking keys to be purchased if further keys are needed (standard supply: 2 units). The keys of all switches have the same code. Other codes on request.</p>

Lock out device

Article	Description
LK S1D001	Lock out device, mounting on the right side of the switch
LK S1S001	Lock out device, mounting on the left side of the switch

Device made entirely of metal, to be fixed on the side of NS switches without any additional plate or support.
The front slider mechanically closes the actuator entry hole and functions as a shield for the RFID receiver antenna on the switch; thus ensuring an additional level of protection against accidental closure of the guard and untimely machine restart.
Allows insertion of up to 5 padlocks with a 3.5 mm arc diameter.

17

 pizzato



Available integrated devices

	Description	Colour	Article	Combinable with contacts ⁽¹⁾	Protrusion (x) mm
	Illuminated button, spring-return	White Red Green Yellow Blue	VN NG-AC27121 VN NG-AC27123 VN NG-AC27124 VN NG-AC27125 VN NG-AC27126	1NO (1NC) (2NO) (1NO+1NC)	3
	Non-illuminated button, spring-return	Black	VN NG-AC27122	1NO (1NC) (2NO) (1NO+1NC)	3
	Non-laser-markable, illuminated, projecting push button ⁽²⁾	Red	VN NG-AC26018	1NO (1NC) (2NO) (1NO+1NC)	6,1
	Indicator light	Red Yellow Green Blue White	VN NG-AC26060 VN NG-AC26061 VN NG-AC26062 VN NG-AC26063 VN NG-AC26064	/	2,7
	Emergency stop button acc. to EN ISO 13850				
	Rotary release Push-pull release	Red Red	VN NG-AC26052 VN NG-AC26055	2NC	26,4
	Emergency stop button for contact blocks with 3 contacts acc. to EN ISO 13850			2NC+1NO	26,4
	Rotary release	Red	VN NG-AC26056		
	Illuminated emergency stop button acc. to EN ISO 13850				
	Rotary release Push-pull release	Red Red	VN NG-AC26051 VN NG-AC26054	2NC	26,4
	Simple stop button				
	Rotary release Push-pull release	Black Black	VN NG-AC26053 VN NG-AC26057	2NC	26,4
	Illuminated selector switch with handle, with transparent lens for LED				
	↙	Black	VN NG-AC26033	1NO 1NC (2NO) (1NO+1NC)	
	↘	Black	VN NG-AC26030		
	↓	Black	VN NG-AC26034		
	↔	Black	VN NG-AC26031		
	Key selector switch, 2 positions				
	↙ ↘	Black	VN NG-AC26043	1NO (1NC) (2NO) (1NO+1NC)	39 (a)
	↙ ↗	Black	VN NG-AC26040		14 (b)
	↙ ↙	Black	VN NG-AC26041		
	Closing cap	Black	VN NG-AC26020	/	2,7
	Fixing key	Black	VN NG-AC26080	/	/

Legend: Maintained Spring-return Key extraction position (a) with key (b) without key

⁽¹⁾ The contacts in brackets are on request. Contact our technical department to verify the effective feasibility of the control panel with the chosen combination of control devices.

⁽²⁾ The projecting buttons are not laser markable.

To order buttons with marking:

add the marking code indicated in the tables on pp. 19-22 to the article codes.

Example: Black spring-return button with "O" engraving.

VN NG-AC27122 → VN NG-AC27122-L1

List of available engravings

Code	Symbol								
L1	○	L42	💡	L27	⌚	L330	▶	L187	◇
L287	⌚	L43	💡	L147	✿	L455	▶▶	L386	➡
L413	▶	L213	☀	L148	▶	L456	■	L230	~~~~~
L2		L254	💡	L162	▶	L369	⬇	L411	➡️
L3		L17	👉	L172	📞	L426	“(”)	L102	☰
L4		L44	👉	L220	📞	L59	⊕	L103	✖
L35	—	L45	👉	L277	⚙	L64	⊕	L139	▶
L36	—	L46	👉	L226	⌚	L62	⊕	L140	⌚
L37	—	L60	⌚	L142	⚠	L63	⊕	L141	⌚
L11	+	L191	⌚	L54	⚡	L86	▶	L157	▶ AIR
L12	—	L193	⌚	L56	⚡	L88	▶	L381	◀
L412	//	L308	⌚	L57	⚡	L89	▶	L445	↑
L188	//	L61	🐌	L55	⚡	L87	▶	L278	▶
L14	钤	L153	🐰	L146	⌚	L76	◇	L323	⌚
L32	钤	L194	🐰	L293	⌚	L77	◇	L362	▶
L33	钤	L309	🐰	L304	🔒	L78	⊕	L380	⌚
L34	钤	L408	!	L305	🔓	L190	⌚	L382	⌚
L240	钤	L145	▶	L470	▶	L416	⌚	L383	▶
L16	💡	L336	▶	L317	▶	L417	⌚	L384	▶
L41	💡	L96	“(”)	L319	⬇	L189	○	L385	◀

Other engravings on request

Code	Symbol								
L7	↑	L25	↓	L84	↔	L174	↔	L316	⟳
L8	↓	L30	⚡	L90	⤒	L175	⤓	L394	⤔
L9	⬅	L31	⤒	L91	⤓	L176	⤓	L399	⤔
L10	➡	L58	⤒	L312	⤒⤓	L294	⤓	L436	▲
L18	⤒⤓	L75	⤒	L311	⤒⤓	L313	↑	L437	▼
L143	⤒⤓	L425	⤒⤓	L442	⤒⤓	L314	↓	L438	▶
L24	↗	L454	↖	L443	↓	L227	⤓	L439	⤔
L310	↖	L83	↗	L170	⤓	L228	⤒	L440	⤔

L234	⤒⤓	L241	⤒⤓	L247	⤒⤓	L279	⤒⤓	L392	⤒⤓	L467	⤒⤓
L235	⤒⤓	L242	⤒⤓	L248	⤒⤓	L280	⤒⤓	L393	⤒⤓	L468	⤒⤓
L236	⤒⤓	L243	⤒⤓	L251	⤒⤓	L375	⤒⤓	L463	⤒⤓		
L237	⤒⤓	L244	⤒⤓	L252	⤒⤓	L389	⤒⤓	L464	⤒⤓		
L238	⤒⤓	L245	⤒⤓	L253	⤒⤓	L390	⤒⤓	L465	⤒⤓		
L239	⤒⤓	L246	⤒⤓	L260	⤒⤓	L391	⤒⤓	L466	⤒⤓		

Other engravings on request

Code	Symbol	Code	Symbol	Code	Symbol	Code	Symbol	Code	Symbol	Code	Symbol
L28	STOP	L67	3	L39		L289	BOOST	L208		L135	AVANTI-INDIETRO
L50		L68	4	L114		L292	MONO / TRI	L117	POMPA FILTRO 0-1	L104	24V 电源指示 24V Power
L48		L69	5	L306		L327	ENABLE DISABLE	L118	FILTER PUMP 0-1	L105	220V 电源指示 220V Power
L49		L70	6	L130	100%	L222	ACCESS DENIED	L119	RISCALDAMENTO 0-1	L106	选择开关 Selector
L113		L71	7	L315	24V=	L223	ACCESS ALLOWED	L120	HEATING 0-1	L107	启动按钮 START
L29	START	L72	8	L82	ERONDUND	L224	ACCESS REQUEST	L121	SCATTO TERMICO	L108	停止按钮 STOP
L53		L73	9	L199	SPEED	L225	ACCESS RESET	L122	CIRCUIT BREAKER	L109	电源指示 Power
L51		L74	0	L233	CAUTION	L215	INIT	L123	MAN. - AUT.	L110	合闸指示 Ready
L52		L450	-1	L250	POWER	L216	C / C	L124	START CICLO	L111	故障指示 Stoppage
L218		L451	-2	L332	ALLOW IN	L370	UNLOCK DOOR	L125	RADDRIZZATORE 0-1		
L276		L129	3/4	L334	SYSTEM START	L371	REQUEST / RESET ACCESS TO AREA	L126	STOP CICLO		
L410	PAUSE (START)	L15	R	L335	SYSTEM STOP	L205		L127	BY-PASS EMERGENZE 0-1		
L65	1	L40	R	L333	CYCLE STOP	L206		L131	AZIONAMENTO 0-1		
L66	2	L38	R	L281	DEFAULT	L207		L132	TACITAZIONE SIRENA		

Other engravings on request



List of available engravings – TEXTS

Code	Text	Code	Text	Code	Text	Code	Text
IT0	ARRESTO	GB0	STOP	FR0	ARRÊT	DE0	HALT
IT1	AVVIO	GB1	START	FR1	MARCHE	DE1	START
IT2	CHIUSO	GB2	CLOSE	FR2	FERMÉ	DE2	ZU
IT3	SU	GB3	UP	FR3	MONTÉE	DE3	AUF
IT4	GIÙ	GB4	DOWN	FR4	DESCENTE	DE4	AB
IT5	SPENTO	GB5	OFF	FR5	ARRÊT	DE5	AUS
IT6	ACCESO	GB6	ON	FR6	MARCHE	DE6	EIN
IT7	IN SERVIZIO	GB7	RUN	FR7	EN SERVICE	DE7	BETRIEB
IT8	ERRORE	GB8	FAULT	FR8	PANNE	DE8	STÖRUNG
IT9	TEST	GB9	TEST	FR9	ESSAI	DE9	PRÜFUNG
IT10	SPENTO ACCESO	GB10	OFF ON	FR10	ARRÊT MARCHE	DE10	AUS EIN
IT11	MAN. AUTO	GB11	MAN. AUTO	FR11	MAN. AUTO	DE11	HAND AUTO
IT12	MAN. 0 AUTO	GB12	MAN. 0 AUTO	FR12	MAN. 0 AUTO	DE12	HAND 0 AUTO
IT13	MARCIA	GB13	DRIVE	FR13	MARCHE	DE13	ANTRIEB
IT14	RIAVVIA	GB14	RESET	FR14	REARM.	DE14	ENTSPERREN
IT15	AVANTI	GB15	FORWARD	FR15	AVANT	DE15	VORWÄRTS
IT16	INDIETRO	GB16	REVERSE	FR16	ARRIÈRE	DE16	RÜCKWÄRTS
IT17	AUMENTA	GB17	RAISE	FR17	MONTER	DE17	HEBEN
IT18	DIMINUISCI	GB18	LOWER	FR18	DESCENDRE	DE18	SENKEN
IT19	SINISTRA	GB19	LEFT	FR19	GAUCHE	DE19	LINKS
IT20	DESTRA	GB20	RIGHT	FR20	DROITE	DE20	RECHTS
IT21	FRENO	GB21	BRAKE	FR21	FERMER/OUVRIR	DE21	BREMSEN
IT22	ALTO	GB22	HIGH	FR22	HAUT	DE22	HOCH
IT23	BASSO	GB23	LOW	FR23	BAS	DE23	NIEDRIG
IT24	VELOCE	GB24	FAST	FR24	RAPIDE	DE24	SCHNELL
IT25	LENTO	GB25	SLOW	FR25	LENT	DE25	LANGSAM
IT26	PIÙ VELOCE	GB26	FASTER	FR26	PLUS RAPIDE	DE26	SCHNELLER
IT27	PIÙ LENTO	GB27	SLOWER	FR27	PLUS LENT	DE27	LANGSAMER
IT32	APRIRE	GB32	OPEN	FR32	OUVRIR	DE32	ÖFFNEN
IT63	CHIAMATA	GB63	CALL	FR63	APPEL	DE63	ANRUF
IT64	OCCUPATO	GB64	OCCUPIED	FR64	OCCUPÉ	DE64	BESETZT
IT99	ARRESTO D'EMERGENZA	GB99	EMERGENCY STOP	FR99	ARRÊT D'URGENCE	DE99	NOT-AUS


Other engravings on request




General Catalogue
Detection



General Catalogue
HMI



General Catalogue
Safety



General Catalogue
Lift



Website
www.pizzato.com



PASSION FOR QUALITY

Pizzato Elettrica s.r.l. via Torino, 1 - 36063 Marostica (VI) Italy
Phone: +39 0424 470 930
E-mail: info@pizzato.com
Website: www.pizzato.com

ZE FGL24A21-ENG



8 018851 572043

Any information or application example, connection diagrams included, described in this document are to be intended as purely descriptive. The choice and application of the products in conformity with the standards, in order to avoid damage to persons or goods, is the user's responsibility. The drawings and data contained in this document are not binding and we reserve the right, in order to improve the quality of our products, to modify them at any time without prior notice. All rights to the contents of this publication are reserved in accordance with current legislation on the protection of intellectual property. The reproduction, publication, distribution and modification, total or partial, of all or part of the original material contained therein (including, but not limited to, texts, images, graphics), whether on paper or in electronic form, are expressly prohibited without written permission from Pizzato Elettrica Srl. All rights reserved. © 2021 Copyright Pizzato Elettrica.